



AD-4x Distributed Audio System

The AD-4x is perfect for residential or commercial installations that require music everywhere - without breaking the budget. This compact audio distribution system contains both a matrix switching pre-amp and a built-in power amplifier. The four local source inputs can be augmented with four remote source inputs, making it easy to listen to music from your kitchen iPod dock or office PC.

The second generation of the AD-4 audio distribution system, the AD-4x has added powerful new features, providing more flexibility and quicker installations. Now with pre-outs for each zone, a separate amplifier may be added for additional power and speakers where needed. The addition of Ethernet support allows two-way control via the LAN, while a web interface allows the AD-4x output zones to be tested during installation via a web browser on a smartphone, tablet or PC. This web interface is also used to configure output zones into groups, allowing them to be controlled as a single zone.

Designed to be a seamless extension of an RTI control system, the AD-4x provides the audio switching, amplification and distribution functions, while RTI central processors and user interfaces manage the audio source control, user input and status feedback. Information such as the selected source, volume level, and tone control settings are available for each zone.

Audio Distribution Accessories



*PDM-1
Phone/Doorbell
Module*



*RSP-1
Remote Source
Wall Plate*



*RTI Amplifiers
CP-450 4 Channel - 50W/Ch
CP-1650 16 Channel - 50W/Ch*

RTI User Interfaces



Key Features

- Four analog stereo audio output zones with pre-outs.
- Four analog audio source inputs with independent trim level adjustment.
- Independent volume and tone control for all audio zones.
- Ethernet support and a web interface allows the AD-4x output zones to be tested during installation via a web browser on a smartphone, tablet or PC.
- Configure output zones into groups, allowing them to be controlled as a single zone.
- Accessory wall plate (RSP-1) allows source equipment to be connected remotely with a Cat-5 cable.
- Controlled via IR, or two-way control via RS-232 and IP using RTI control systems.
- Twenty-five watts per channel in each zone.
- Optional phone and doorbell mute function using accessory wall plate (PDM-1).
- Zone power indicator LEDs.
- Compact, low-profile IU design.

Call 952-253-3100

www.rticorp.com



It's Under Control®

Specifications

AC Input Voltage	115VAC or 240VAC (Switchable), 230W
Power switch.....	Front Panel On/Off control with LED power indicator
Mounting.....	Rack mount or free standing
Dimensions (with rack ears & front cover) HxWxD.....	2.1in(53mm) x 19in(482mm) x 13.3in(340mm)
Dimensions Chassis (without rack ears & front cover)HxWxD.....	2.1in(53mm) x 16.9in(430mm) x 13.3in(340mm)
Weight	11 lbs (5kg)
Operating Temperature.....	C -10 to +40 degrees F +14 to +104 degrees
Local Input Source.....	Four, RCA jacks
Remote Input mixed Source.....	Four, RJ-45 jacks
CRTL In	One, 3.5mm jack, for IR control
Remote Source IR Input	One, 3.5mm jack x 4, for IR input
RS232 Port.....	One, Bidirectional control
Ethernet Port.....	One, RJ45 Bidirectional control
Trigger Output (Status)	One, 12VDC@15mA
Voltage Output.....	One, 12VDC@500mA
Mute.....	3.5mm jack
Doorbell Input Sensitivity (PDM1)	AC/DC 3-12V
Phone input sensitivity (PDM1)	AC25-100V/20Hz
Output Zones.....	Four zones, two channels each
Rated Power / Channel.....	>20 Watts, 20Hz to 20KHz
.....	(RMS, 2 channels driven into 8 ohms)
Power/Channel	>25 Watts @1KHz
.....	(RMS, 2 channels driven into 8 ohms)
Total Harmonic Distortion @20W/8 ohm	0.5%.
Total Harmonic Distortion @1W/8 ohm.....	<0.05%.
S/N @ Rated power, IEC A-wtd, Source input shorted	92dB (mute +1)
Frequency Response 20Hz to 20KHz @1W/8 ohms.....	1.5+/-0.5dB
Input Overload.....	2.5V
Input Impedance.....	>22K ohms
Channel separation @1KHz.....	>60dB
Crosstalk Between Sources @rated power /1KHz	>75dB
Crosstalk Between Zones @rated power /1KHz	80dB
Treble control @10KHz.....	10dB +/-0.5dB
Bass control range @100Hz.....	10dB +/-0.5dB
Warranty.....	One Year (Parts & Labor)

All features and specifications subject to change without notice



Rear view

5775 12th Avenue East, Suite 180, Shakopee, MN 55379
 PH: (952) 253-3100 • Website: www.rticorp.com

RTI Accessories

RSP-1	Remote Source Connection Plate
PDM-1	Phone/Doorbell Mute Interface
RTiDock	Dock for Apple iPod®
CP-450	4 Channel Amplifier
CP-1650	16 Channel Amplifier



Other RTI Products

Virtual Panel	PC Software Interface (App)
RTiPanel	Mobile Software Interface (App)
SURFiR	Companion Remote Control
T1-B+	Remote Control
T2-Cs+	Remote Control
T2i	Remote Control
T2x	Remote Control
T3-V+	Remote Control
RKM-1+	In-Wall Audio Distribution Keypad
RK1+	2-4-8 Button In-Wall Keypad
KX2	2.8 inch In-Wall Touchpanel Keypad
RK3-V	3.5 inch In-Wall Touchpanel Keypad
KX7	7 inch In-Wall Touchpanel
CX7	Countertop/Under-Cabinet Touchpanel
AD-8x	Distributed Audio System
RP-4	RF Control Processor
XP-3	Advanced Control Processor
XP-6	Advanced Control Processor
XP-8s	Advanced Control Processor
CB-8	Touchpanel Connecting Block
CM-232	RS-232 Communication Module
CPB-1	Control Port Connecting Block
ECB-5	IR Connecting Block
ESC-2	Ethernet Serial Converter
IPE-4	IR Port Expander
PCM-4	Port Control Module
RCM-4	Ethernet Relay Module
vIRsa Mouse	IR Emitter



Integration Designer® Programming Software



It's Under Control®